



LED T8 Ballast Compatibility Chart

Ballast Brand*	Part Number	# Of Lamps	Start Method	Lamp Connection	Enclosed Fixture	1 Lamp		2 Lamps		3 Lamps		4 Lamps		Ballast Type	Factor Value
						120V	277V	120V	277V	120V	277V	120V	277V		
Philips-Advance	VEL-3P32-SC	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.88
Philips-Advance	IOPA-2P32-LW-N	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	L	N/A
Philips-Advance	IOP-1P32-LW-N	1	IS	N/A	Yes	✓	P	-	-	-	-	-	-	L	0.77
Philips-Advance	IOP-1P32-SC	1	IS	N/A	Yes	✓	✓	-	-	-	-	-	-	N	0.87
Philips-Advance	IOP-1P32-LW-SC	1	IS	N/A	Yes	✓	✓	-	-	-	-	-	-	L	0.77
Philips-Advance	IOP-3PSP32-SC	3	PS	Parallel	Yes	-	-	N/A	N/A	✓	✓	-	-	N	0.88
Philips-Advance	IOP-4PSP32-SC	4	PS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.89
Philips-Advance	IOP-4PSP32-LW-SC	4	PS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	L	0.69
Plusrite	BAF232IS/MV	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.89
Plusrite	BAF332IS/MV	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.88
Plusrite	BAF332IS/MV/L	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	L	0.78
Plusrite	BAF432IS/MV	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.88
Plusrite	BAF432IS/MV/L	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	L	0.78
Prolume	EP232IS/L/MV/SL	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	L	0.78
Prolume	E432IS/120/R/SL	4	IS	Parallel	Yes	-	-	-	-	N/A	-	N/A	-	N	0.87
Sola	E-758-U-232-MC	2	IS	Parallel	Yes	✓	P	✓	✓	-	-	-	-	N	0.88
Sunpark	120-1/32IS HPF	1	IS	N/A	Yes	P,T	N/A	-	-	-	-	-	-	N	0.88
Sunpark	U-2/32ISE-LBF	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	L	0.78
Sunpark	U-3/32ISE	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.88
Sunpark	120-3/32IS MPF	3	IS	Parallel	Yes	-	-	✓	N/A	✓	N/A	-	-	N	0.88
Sunpark	U-4/32IS HP,F	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.88
Sunpark	U-4/32ISE-LBF	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	L	0.77
Sunpark	U-1/32PSE	1	PS	N/A	Yes	✓	✓	-	-	-	-	-	-	N	0.88
Sunpark	SL15T	2	RS	Parallel	Yes	N/A	N/A	P,T	N/A	-	-	-	-	N	0.88
Sunpark	LC 12013T	1	PS	N/A	Yes	P,T	N/A	-	-	-	-	-	-	N/A	
Superior Life	70210	2	PS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.88
Superior Life	70211	4	PS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.87
Sylvania	QT 3x32/277 IS	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.9
TCP	E3P32ISUNVE	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.88
TCP	E4P32ISUNVE	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.88
Universal Lighting Technologies	B232IUNVHP-N	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.88
Universal Lighting Technologies	B232IUNVEL-A	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	L	0.77
Universal Lighting Technologies	B233IUNVHE-A	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.87
Universal Lighting Technologies	B432IUNVHE L-A	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	L	0.77
Universal Lighting Technologies	B332IUNVHP-A	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.88
Universal Lighting Technologies	B432IUNVHP-A	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.88
Universal Lighting Technologies	B232I120RES-A	2	IS	Parallel	Yes	✓	N/A	✓	N/A	-	-	-	-	N	0.88
Universal Lighting Technologies	B232IUNVHP-B	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.88
Universal Lighting Technologies	B432IUNVHE-A	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.87
Universal Lighting Technologies	B432IUNVHEH-E	4	IS	Parallel	No	-	-	-	-	✓	✓	✓	✓	H	1.15
Universal Lighting Technologies	B232I277RH-A	4	IS	Parallel	No	-	-	-	-	N/A	P,T	N/A	✓	H	1.09
Universal Lighting Technologies	B132IUNVEL-A	1	IS	N/A	Yes	✓	✓	-	-	-	-	-	-	L	0.77
Universal Lighting Technologies	B432PUNVHE-A	4	PS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.87
Universal Lighting Technologies	B232PUNVHE-B	2	PS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.88
Universal Lighting Technologies	B332PUNVHE-A	3	PS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.88
Universal Lighting Technologies	B232SR277S30	2	RS	Parallel	Yes	N/A	N/A	N/A	✓	-	-	-	-	N/A	
Watran	DB-232N-MV-TP-HE	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.87
Watran	DB-332N-MV-TP-HE	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.87
Watran	DB-432N-MV-TP-HE	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.87
Watran	DB-432L-MV-TP-HE	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	L	0.77
Watran	DB-232N-MV-TP-HE (SC)	2	IS	Parallel	Yes	✓	✓	✓	✓	-	-	-	-	N	0.87
Work Horse	WHS63-UNV-T8-IS	3	IS	Parallel	Yes	-	-	✓	✓	✓	✓	-	-	N	0.99
Work Horse	WHS64-UNV-T8-IS	4	IS	Parallel	Yes	-	-	-	-	✓	✓	✓	✓	N	0.96

Ballast Brand*	Part Number	# Of Lamps	Start Method	Lamp Connection	Enclosed Fixture	1 Lamp		2 Lamps		3 Lamps		4 Lamps		Ballast Type	Factor Value
						347V	480V	347V	480V	347V	480V	347V	480V		
General Electric	GE432MAX347-N	4	IS	Parallel	Yes	-	-	-	-	✓	-	✓	-	N	0.94
Osram	QHE 2x32T8/347 PSN-SC	2	PRS	Parallel	Yes	✓	-	✓	-	-	-	-	-	N	0.88
Osram Sylvania	QT 2x32/347 ISH-SC	2	IS	Parallel	No	NA	-	✓	-	-	-	-	-	H	1.2
Sylvania	QT 4X32/347LP	4	IS	Parallel	Yes	-	-	-	-	T	-	T	-	N/A	N/A
Universal Lighting Technologies	B432I347HE-A	4	IS	Parallel	Yes	-	-	-	-	✓	-	✓	-	N	0.88

Applies to the following Satco products:

S49934, S49935, S49936, S49937, S49946, S49947, S49948, S49949, S49975, S49976, S49977, S49978, S49990, S49991, S49992, S49993, S11740, S11741, S11742, S11743

P PF <0.85
T THD >30%
NC Not compatible
NA Not applicable
****** Dimmable Ballast

Ballast Factors:
 L - Low
 N - Normal
 H - High

This list is current as of Jan. 2022. We are continuously testing for compatible ballasts. Please check back for updates.

* All trademarks are the property of their respective owners